

Two Rooms (3/1) -EVO Pre-Program: F6

Two Room, 3-Zone, 2 Daylight Zone & 1-Zone, 1-Daylight Zone															
Photo sensor inputs for 2 daylight zone in the 3-zone room and 1 daylight sensor in the 1-zone room, motion sensor inputs for Occupancy on at 50% or Vacancy control, Remote digital CAT-5 LightSync G3 MZD or standard button switches for local room control															
Node	Output:	EVO Photocells		EVO Inputs - 24V Motion Sensor				Remote LightSync Input Devices				On/Off Push Button Non-Dim			
Address:	Relay #	PC-1	PC-2	IN-1	IN-2	IN-3	IN-4	LS-G3 MZD3	LS-G3 MZD2	LS-G3 MZD1	LS-G3 MZD1	LS-G3 1ZND	LS-G3 1ZND	LS-G3 1ZND	LS-G3 1ZND
F 6	Dimmer #	LS: 01	LS: 02	LS: 03.1	LS: 03.2	LS: 03.3	LS: 03.4	LS: 04/05	LS: 06/07	LS: 08	LS: 09	LS: 0A	LS: 0B	LS: 0C	LS: 0D
	Relay 1 Dim 01.1			Occ-on/off On-50%	Vacancy-off			PB:1-on/off Ramp Up/Dn	PB:1-on/off Ramp Up/Dn			On/Off Togg.	On/Off Togg.		
MSB / LSB	Relay 2 Dim 01.2	-10% scale		Occ-on/off On-50%/PC1	Vacancy-off			PB:2-on/off Ramp Up/Dn	PB:2-on/off Ramp Up/Dn			On/Off Togg.	On/Off Togg.		
	Relay 3 Dim 01.3	Full scale		Occ-on/off On-50%/PC1	Vacancy-off			PB:3 on/off Ramp Up/Dn			PB:1-on/off Ramp Up/Dn	On/Off Togg.		On/Off Togg.	
	Relay 4 Dim 01.4		Full Scale			Occ-on/off On-50%/PC2	Vacancy-off				PB:1-on/off Ramp Up/Dn				On/Off Togg.
								PB:4-Off R1-3	PB:3-Off R1,2	MZD1 & 1ZND operation can be used for G3 or G2 switches					

Additional G3 switch addresses for 3-Way operation															
3 or 2 zone Private or Open Office Code Compliant Room Type - CA, Title-24: CD 0007, 0012 Ashrae 90.1: CD 0207 0212 IECC: CD 0407, 0412															
Node	Output:	Additional Inputs				Additional G3 Switches for 3-Way operation									
Address:	Relay #	LS-	LS-	LS-	LS-	LS-	LS-	LS-G3 MZD3	LS-G3 MZD2	LS-G3 MZD1	LS-G3 MZD1	LS-G3 1ZND	LS-G3 1ZND	LS-G3 1ZND	LS-G3 1ZND
F 6	Dimmer #	LS:	LS:	LS:	LS:	LS:	LS:	LS: 14/15	LS: 16/17	LS: 18	LS: 19	LS: 1A	LS: 1B	LS: 1C	LS: 1D
	Relay 1 Dim 01.1							PB:1-on/off Ramp Up/Dn	PB:1-on/off Ramp Up/Dn			On/Off Togg.	On/Off Togg.		
MSB / LSB	Relay 2 Dim 01.2							PB:2-on/off Ramp Up/Dn	PB:2-on/off Ramp Up/Dn			On/Off Togg.	On/Off Togg.		
	Relay 3 Dim 01.3							PB:3-on/off Ramp Up/Dn			PB:1-on/off Ramp Up/Dn	On/Off Togg.		On/Off Togg.	
	Relay 4 Dim 01.4									PB:1-on/off Ramp Up/Dn					On/Off Togg.
								PB:4-Off R1-3	PB:3-Off R1,2	MZD1 & 1ZND operation can be used for G3 or G2 switches					